

3.0 A Fast Recovery Silicon Rectifier
Rectifier Reverse Voltage 50 to 1000V




Features

- Diffused junction
- Fast switching for high efficiency
- High current capability and low Forward Voltage Drop
- Surge overload rating to 100A peak
- Low reverse leakage current
- Plastic material has UL flammability classification 94V-0

Mechanical Data

Case: Molded plastic
 Terminals: Solder plated solderable per MIL-STD-202, Method 208
 Polarity: Cathode band
 Mounting Position: Any
 Weight: 1.1 grams (approx)

DO-27



All dimensions inches and (millimeters)

Maximum Ratings & Thermal Characteristics

Rating at 25°C ambient temperature unless otherwise specified, Resistive or Inductive load, 60 Hz.
 For Capacitive load derate current by 20%.

Parameter	Symbol	BY396	BY397	BY398	BY399	unit
Maximum repetitive peak reverse voltage	VRRM	100	200	400	800	V
Maximum RMS bridge input voltage	VRMS	70	140	280	560	V
Maximum DC blocking voltage	VDC	100	200	400	800	V
Maximum average forward rectified output current at TA=75°C	IF(AV)	3.0				A
Peak forward surge current single sine-wave superimposed on rated load (JEDEC Method)	IFSM	200				A
Maximum reverse recovery time TJ=25°C	Trr	150		150	500	nS
Typical thermal resistance per element	ReJA	20				°C/W
Typical junction capacitance per element	Cj	28				pF
Operating junction and storage temperature range	TJ, TSTG	-55 to + 150				°C

Electrical Characteristics

Rating at 25°C ambient temperature unless otherwise specified. Resistive or Inductive load, 60Hz.
 For Capacitive load derate by 20 %.

Parameter	Symbol	BY396	BY397	BY398	BY399	Unit
Maximum instantaneous forward voltage drop per leg at 3.0A	VF	1.3				V
Maximum DC reverse current at rated DC blocking voltage per element	IR		10 100			μA

Rating and Characteristic Curves (TA=25°C Unless otherwise noted) BY396 thru BY399

Fig. 1 Reverse Recovery Time and Test Circuit Diagram




Fig. 2 Derating Curve for Output Rectified Current




Fig. 3 Peak Forward Surge Current




Fig. 4 Typical Instantaneous Forward Characteristics




Fig. 5 Typical Reverse Characteristics

